

Powersafe Lug Convertor

This device allows a standard cable lug to be temporarily or permanently terminated to a Powersafe connector.

The cable lug is simply bolted to the Powersafe electrical contact and the connector assembled as normal.

The Convertors come in 2 x sizes, suitable for cable lugs with M12 through holes for cable sections of 25- 150mm² and 185-300mm² cables. (300mm² requires a contained palm lug).



For use with 25-150mm² cables



For Use with 185-300mm² cables



Key Features include:

- Facilitates standard cable crimp lugs
- IP67 when mated
- Up to 800Amp operation
- No special tools required.
- Lugs can be quickly terminated to the connector.
- Suitable as temporary or permanent connection.
- No adaptors so insulator mechanical and electrical properties are maintained.

Part Number	Description	Part Number	Description
SLCS001	Lug Convertor S150 Source E-GN	SLCS006	Lug Convertor S300 Source E-GN
SLCS002	Lug Convertor S150 Source N-BL	SLCS007	Lug Convertor S300 Source N-BL
SLCS003	Lug Convertor S150 Source 1-BN	SLCS008	Lug Convertor S300 Source 1-BN
SLCS004	Lug Convertor S150 Source 2-BK	SLCS009	Lug Convertor S300 Source 2-BK
SLCS005	Lug Convertor S150 Source 3-GY	SLCS010	Lug Convertor S300 Source 3-GY
SLCD001	Lug Convertor D150 Drain E-GN	SLCD006	Lug Convertor D300 Drain E-GN
SLCD002	Lug Convertor D150 Drain N-BL	SLCD007	Lug Convertor D300 Drain N-BL
SLCD003	Lug Convertor D150 Drain 1-BN	SLCD008	Lug Convertor D300 Drain 1-BN
SLCD004	Lug Convertor D150 Drain 2-BK	SLCD009	Lug Convertor D300 Drain 2-BK
SLCD005	Lug Convertor D150 Drain 3-GY	SLCD010	Lug Convertor D300 Drain 3-GY